



MINI AMP-IN BOARD-IN TERMINALS

PCB DESIGN FLEXIBILITY AND ASSEMBLY EFFICIENCY

TE Connectivity (TE)'s Mini AMP-IN board-in terminals enrich printed circuit board (PCB) designs by supporting flexible PCB layouts and providing a more efficient assembly process. The compact Mini AMP-IN terminals are available to support one of the most common wire and through hole sizes, including 26-12AWG wires and 1.85-3.55mm through holes. They offer easier, more efficient assembly with a dual lance structure that stabilizes the contacts in the PCB during the soldering process. The Mini AMP-IN board-in contacts are sold without housings, making them more compact than other wire-to-board connectors and enabling greater PCB design flexibility.

ELECTRICAL

- Voltage Rating: 250 VAC
- Current rating: Based on wire specification

MECHANICAL

- Hole Size: 1.85-3.55mm
- Wire size: 26-12 AWG
- PCB Thickness: 1.6 ± 0.05 mm

MATERIALS

- Pre-tin copper alloy
- Operating Temperature: -40 to +105°C

PRODUCT COMPLIANCE/ CERTIFICATION

- UL_E13288_20220718
- ROHS, REACH compliance

FEATURES

- Available in 26-12AWG wire to cover one of the most common board-in applications
- Double lance structure provides excellent retention force to stabilize contact during soldering
- Compact terminal without housing enables flexible printed circuit board (PCB) designs
- More secure supply-chain helps ensure reliable product availability

ADDITIONAL RESOURCES

- Product Specification: [108-106642](#)
- Application Specification: [114-106642](#)
- [Mini AMP-IN Products Quick Reference Guide](#)

APPLICATIONS



Air Conditioner Unit



Motor



Air purifier

MINI AMP-IN BOARD-IN TERMINALS

MINI AMP-IN BOARD-IN CONTACTS

Wire Range (AWG)	PCB Hole Size (mm)	Part Number
26-22	1.85±0.05	2393261-1
22-18	1.85±0.05	2393199-1
18-16	2.4±0.05	2393222-1
14	2.55±0.05	2393227-1
12	3.55±0.05	2393237-1

Connect With Us

We make it easy to connect with our experts and are ready to provide all the support you need. Visit [te.com/support](#) to chat with a Product Information Specialist.

[te.com/mini-amp-in-board-in-terminals](#)

TE Connectivity, TE connectivity (logo), TE and AMP-IN are trademarks owned or licensed by the TE Connectivity plc family of companies. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

While TE has made every reasonable effort to ensure the accuracy of the information in this document, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any changes to the information contained herein without prior notice. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect, or consequential damages arising out of the sale, resale, use, or misapplication of the product. TE expressly disclaims any implied warranties with respect to the information contained herein, including, but not limited to, implied warranties of merchantability or fitness for a particular purpose. Dimensions, specifications and/or information contained herein are for reference purposes only and are subject to change without notice. Consult TE for the latest dimensions, specifications and/or information. Users of TE Connectivity products must make their own assessment as to whether the respective product is suitable for the respective desired application.

© 2025 TE Connectivity. All Rights Reserved.

08/25